

131s Graphic EQ

Single 31-Band Equalizer

dbx[®]
by HARMAN



Exceptional sound and rugged reliability

When the pros need an EQ, they turn to dbx. With a proven track record that spans four decades, dbx[®] EQ's are the industry standard for touring, studios, and audio installations. With the dbx heritage of revered pro EQs, the 131s meets the needs of the most demanding sound reinforcement environments, while offering the simplicity of straightforward controls.

The dbx 131s includes a single 31-band channel of 1/3-octave equalization, ± 12 dB input gain, switchable ± 6 dB or ± 12 dB boost/cut range, 20mm nonconductive sliders, an intuitive user interface, and output level metering. From its extended 10Hz to 50kHz frequency response and 110 dB dynamic range to the quality componentry and meticulous attention to detail, the 131s offers exceptional sound and rugged reliability that guarantees you will always sound your best.

Sure to find a home in the studio, on tour and with installed sound venues, the dbx 131s is destined to take its rightful place in the lineage of great dbx signal processors that are the professional's choice in signal processing. With such affordable quality, there's no longer any excuse for compromising your sound.

Features

- ▶ Single 31-band, 1/3-octave Constant Q frequency bands
- ▶ Switchable boost/cut ranges of ± 6 or ± 12 dB
- ▶ Front panel bypass switch
- ▶ ± 12 dB input gain range
- ▶ 4-segment LED ladders for monitoring output levels
- ▶ XLR and TRS Inputs and Outputs
- ▶ Frequency Response of <10 Hz to >50kHz
- ▶ Dynamic range of greater than 108dB

Who uses this product:



BANDS



DJs



SOUND
INSTALLATION



STUDIO

dbx Professional
Products

8760 S. Sandy Pkwy.
Sandy, Utah 84070



1.801.568.7660 PHONE
1.801.568.7662 FAX

1.801.568.7583 INT'L FAX
customer@dbxpro.com

www.dbxpro.com

131s Graphic EQ

Single 31-Band Equalizer



Specifications

INPUTS:

Connectors: 1/4" TRS, female XLR (pin 2 hot)
 Type: Electronically balanced/unbalanced, RF filtered
 Impedance: Balanced 40k Ω , unbalanced 20k Ω
 Max Input Level: >+21dBu balanced or unbalanced
 CMRR: >40dB, typically >55dB at 1kHz

OUTPUTS:

Connectors: 1/4" TRS, male XLR (pin 2 hot)
 Type: Impedance-balanced/unbalanced, RF filtered
 Impedance: Balanced 100 Ω , unbalanced 50 Ω
 Max Output Level: >+21dBu balanced/unbalanced into 2k Ω or greater
 >+18dBm balanced/unbalanced (into 600 Ω)

SYSTEM PERFORMANCE:

Bandwidth: 20Hz to 20kHz, +0.5/-1dB
 Frequency Response: <10Hz to >50kHz, +0.5/-3dB
 Dynamic Range: Typically >112dB
 Signal-to-Noise: Typically >95dB
 THD+Noise: <0.003%
 Interchannel Crosstalk: <-90dB, 20Hz to 20kHz

FUNCTION SWITCHES:

EQ Bypass: Bypasses the graphic equalizer section in the signal path
 Low Cut: Activates the 50Hz 12dB/octave high-pass filter
 Range: Selects either +/- 6dB or +/- 12dB slider boost/cut range

POWER SUPPLY:

Operating Voltage: 100-240VAC 50/60Hz
 Power Consumption: 15W
 Mains Connection: IEC receptacle

PHYSICAL:

Weight: 4.8 lbs. (2.2 kg) Shipping weight 6.2 lbs. (2.8 kg)
 Dimensions: 1.75" (4.4cm) H x 6" (15.24cm) D x 19" (48.26cm) W

dbx engineers are constantly working to improve the quality of our products. Specifications are, therefore subject to change without notice.